




## **Torino 28° Lever**





DESCRIPTION	PRODUCT CODE	CASE
Passage (hall/closet) Both sides always free	TR101	12
Privacy (bed/bath) Locked by push pin. Unlocked by push pin, lever turn, or emergency pin outside	TR102	12
Dummy (closet) Inactive, single-sided, flush mount with two wood screws	TR100	12
Handleset Interior Trim	TR100-H	12

Finishes	Door Handing	<b>Door Thickness</b>	<b>Key Cylinder</b>
15 Satin Nickel	Non-handed	13/8" to 2"	No entry function
26 Polished Chrome			

Strike Plate	Latch	<b>Door Prep</b>	Materials
2 <sup>1</sup> / <sub>4</sub> " x 1 <sup>3</sup> / <sub>4</sub> " full-lip radius corner standard	$2^{1}/_{4}$ " x 1" radius corner faceplate	Crossbore 2 1/8"	All metal parts
		Edgebore 1"	
	Non-adjustable 2 $\frac{3}{8}$ " or 2 $\frac{3}{4}$ "		
	28 degree turn radius		
	<sup>1</sup> / <sub>2</sub> " throw bolt		
	Split Spindle - both sides operate independently		